

USN

--	--	--	--	--	--	--	--	--	--

10EC64

Sixth Semester B.E. Degree Examination, Dec.2015/Jan.2016
Antennas and Propagation

Time: 3 hrs.

Max. Marks:100

**Note: Answer FIVE full questions, selecting
at least TWO questions from each part.**

PART – A

- 1 a. Define directivity. Obtain the relationship between directivity and beam area to show that smaller the beam area, larger is the directivity. (07 Marks)
- b. Define antenna aperture. Derive the relationship between aperture and beam area. (06 Marks)
- c. Show that maximum effective aperture of a short electric dipole is equal to $0.119 \lambda^2$. (07 Marks)

- 2 a. Find the power radiated and the directivity for the following:
 - i) $U = U_m \sin^2 \theta \sin^3 \phi$ $0 \leq \theta \leq \pi$ $0 \leq \phi \leq \pi$
 - ii) $U = U_m \cos^n \theta$ $0 \leq \theta \leq \pi/2$ $0 \leq \phi \leq 2\pi$ (08 Marks)
- b. Obtain the relative field pattern for two isotropic point sources of same amplitude but opposite phase, spaced $\frac{\lambda}{2}$ apart. (08 Marks)
- c. State and explain power theorem. (04 Marks)

- 3 a. Derive the equation for radiation resistance of a short electric dipole. (08 Marks)
- b. Explain the following : i) Folded dipole, ii) Rhombic antenna. (08 Marks)
- c. A half wave dipole radiating in free space is driven by a current of 0.5 amperes at the terminals. Calculate E and H field at a distance 1 km from the antenna at angles of 45° and 90° . (04 Marks)

- 4 a. Obtain the radiation resistance of a small loop antenna. (07 Marks)
- b. Write short notes on: i) Slot antenna, (ii) Patch antenna. (08 Marks)
- c. Find the radiation efficiency of a 1 meter diameter loop of 10 mm diameter copper wire at (i) 1MHz, (ii) 10 MHz. (05 Marks)

PART – B

- 5 a. Determine the length L, H plane aperture and flare angles θ_E and θ_H of a pyramidal horn for which E-plane aperture $a_E = 10 \lambda$. The horn is fed by rectangular waveguide with TE_{10} mode. Let $\delta = 0.2 \lambda$ in the E-plane and 0.375λ in the H-plane. Also find beam width and directivity. (08 Marks)
- b. Write short notes on: i) Lens antenna; ii) Log periodic antenna (08 Marks)
- c. Design a Yagi-Uda six element antenna for operation at 500 MHz with a folded dipole field. What are the lengths of (i) reflector element, (ii) driven element, (iii) four director element? What is the spacing between reflector and driven element? (04 Marks)

- 6 a. Derive an expression for resultant field intensity in the case of a space wave propagation. (10 Marks)
- b. Evaluate the roughness factors for the earth at 10 MHz, if $\sigma = 5$, for ' θ ' equal to (i) 30° , (ii) 45° , (iii) 60° . (05 Marks)
- c. A transmitting antenna of 100 m height radiates 40 kW at 100 MHz uniformly in azimuth plane. Calculate maximum LOS range and strength of the received signal at 16 m high, receiving antenna at a distance of 10 km. At what distance would the signal strength reduce to 1 mV/m? (05 Marks)
- 7 a. Explain the structure of ionosphere. Derive an expression for refractive index of ionospheric layer. (10 Marks)
- b. Define the following with respect to ionospheric propagation:
- i) Critical frequency
 - ii) Virtual height (06 Marks)
- c. Obtain the relationship between maximum usable frequency (MUF) and skip distance. (04 Marks)
- 8 Write short notes on:
- a. Principle of pattern multiplication
 - b. Scanning array
 - c. Embedded antennas
 - d. Ground wave propagation (20 Marks)
